



# MOTORTRONICS™

*Solid State AC Motor Control*

## MVF Series 7.2 kV 630A 800A

**Motortronics** 7.2kV Class, 'Non-Latching' Series of medium voltage three-phase indoor vacuum contactors can be used in power systems with a rated voltage of up to 7.2 kV and can be used for continuous AC operating currents of up to 630 or 800 amperes. Control power for the design is 120VAC.



**Non-Latching** - uses constant-on electromagnetic coils to close, and hold closed the vacuum bottle contacts. When the power to the electromagnetic coil is removed, the vacuum chamber contacts spring open (termed as; electrically held contacts or non-latching contacts).

RATED CURRENT	RATED VOLTAGE	PART NUMBER NON-LATCHING
630A	7.2kV	34-630-3-7200
800A	7.2kV	34-800-3-7200



***Latching and Non-Latching  
BIL 75kV***

***MVF Series Medium Voltage Contactor***

# 7.2kV RATINGS

**RATED CURRENT****630A / 800A**

Rated Voltage	7.2kV RMS
Rated Maximum Closing Current	4,000A / 6,300A
Rated Maximum Breaking Current	3,200A / 5,040A
Interruption - Sym. Unfused Amps	4.8kA
Interruption - Sym. Fused Amps	36.7kA
Rated Operating Voltage	110 ~ 120 VAC
Maximum Capacitive Current	230A
Closing Current - (Non Latching and Latching Models)	≤DC 14 A
Holding Current - (Non Latching models)	DC 0.8 A
Latch Release Current - (Latching Models)	DC 2.5 A
Maximum Control Circuit Hi-Pot Level	2.0kV
Basic Impulse Level (BIL)	75kV
MV Contact Resistance (20°C)	≤ 250μΩ
VCB Contact Closure Synch	≤ 2.0ms
Switch-On Time	≤ 150ms
Switch-Off Time	≤ 50ms
Rated Operating Frequency	300 times/h
Mechanical life	1,000,000 times
Rated Operating Frequency	1,800 CPH
Electrical Life - AC-3	300,000 cycles
Electrical Life - AC-4	100,000 cycles
Weight	32 kg / 71 Lbs

**CORPORATE HEADQUARTERS****Motortronics/Phasetronics**

1600 Sunshine Drive  
 Clearwater, Florida 33765 USA  
 Tel: 727.573.1819 or 888.767.7792  
 Fax: 727.573.1803 or 800.548.4104  
 E-mail: sales@motortronics.com  
 www: motortronics.com

**INTERNATIONAL LOCATIONS****Motortronics Int'l Korea Co Ltd**

601, Daeryung Techno Tower 5-cha  
 Gasan-dong, Geumcheon-gu  
 Seoul, Korea 9153-774  
 Tel: 82-2-867-5808  
 Fax: 82-2-867-6004  
 www: motortronics-korea.com



**MOTORTRONICS™**  
 Solid State AC Motor Control

**M & P Machinery & Electronics Control**

32 Jiaxin Road, Jimo  
 Qingdao, China 266229  
 Tel: 86-532-81725028  
 Fax: 86-532-81725038  
 www: mp-cn.com

**PN: MT-CTR7P2A-022118**