



MOTORTRONICS™

Solid State AC Motor Control

MVF Series 7.2 kV 630A 800A

Motortronics 7.2kV Class, 'Non-Latching' Series of medium voltage three-phase indoor vacuum contactors can be used in power systems with a rated voltage of up to 7.2 kV and can be used for continuous AC operating currents of up to 630 or 800 amperes. Control power for the design is 120VAC.



Non-Latching - uses constant-on electromagnetic coils to close, and hold closed the vacuum bottle contacts. When the power to the electromagnetic coil is removed, the vacuum chamber contacts spring open (termed as; electrically held contacts or non-latching contacts).

RATED CURRENT	RATED VOLTAGE	PART NUMBER NON-LATCHING
630A	7.2kV	34-630-3-7200C
800A	7.2kV	34-800-3-7200C



***Latching and Non-Latching
BIL 75kV***

MVF Series Medium Voltage Contactor

7.2kV RATINGS

RATED CURRENT**630A / 800A**

Rated Voltage	7.2kV RMS
Rated Maximum Closing Current	4,000A / 6,300A
Rated Maximum Breaking Current	3,200A / 5,040A
Interruption - Sym. Unfused Amps	4.8kA
Interruption - Sym. Fused Amps	36.7kA
Rated Operating Voltage	110 ~ 120 VAC
Maximum Capacitive Current	230A
Closing Current - (Non Latching and Latching Models)	≤DC 14 A
Holding Current - (Non Latching models)	DC 0.8 A
Latch Release Current - (Latching Models)	DC 2.5 A
Maximum Control Circuit Hi-Pot Level	2.0kV
Basic Impulse Level (BIL)	75kV
MV Contact Resistance (20°C)	≤ 250μΩ
VCB Contact Closure Synch	≤ 2.0ms
Switch-On Time	≤ 150ms
Switch-Off Time	≤ 50ms
Rated Operating Frequency	300 times/h
Mechanical life	1,000,000 times
Rated Operating Frequency	1,800 CPH
Electrical Life - AC-3	300,000 cycles
Electrical Life - AC-4	100,000 cycles
Weight	32 kg / 71 Lbs

CORPORATE HEADQUARTERS

Motortronics/Phasetronics
 1600 Sunshine Drive
 Clearwater, Florida 33765 USA
 Tel: 727.573.1819 or 888.767.7792
 Fax: 727.573.1803 or 800.548.4104
 E-mail: sales@motortronics.com
 www: motortronics.com

INTERNATIONAL LOCATIONS

Motortronics Int'l Korea Co Ltd
 601, Daeryung Techno Tower 5-cha
 Gasan-dong, Geumcheon-gu
 Seoul, Korea 9153-774
 Tel: 82-2-867-5808
 Fax: 82-2-867-6004
 www: motortronics-korea.com



MOTORTRONICS™
 Solid State AC Motor Control

M & P Machinery & Electronics Control
 113 Zaoshan Road
 Qingdao, China 266100
 Tel: 86-532-87660633
 Fax: 86-532-87660733
 www: mp-cn.com

PN: MT-CTR7P2A-081314